

AMENDMENTS TO THE CLAIMS

1. (Currently amended) A radio-frequency receiver comprising:
a mixer for mixing a received radio-frequency signal with a local signal to convert the radio-frequency signal into an intermediate-frequency signal or baseband signal;
a local signal generator including a frequency multiplier circuit;
a level switcher for switching an output signal level of the ~~local signal generator~~ frequency multiplier circuit; and
a controller for controlling the level switcher according to a frequency of the received signal.

2. (Original) A radio-frequency receiver as claimed in claim 1,
wherein the local signal generator comprises a voltage-controlled oscillator and a frequency multiplier circuit for multiplying a frequency of an output signal of the voltage-controlled oscillator.

3. (Currently amended) ~~A radio-frequency receiver as claimed in claim 2,~~ A radio-frequency receiver comprising:
a mixer for mixing a received radio-frequency signal with a local signal to convert the radio-frequency signal into an intermediate-frequency signal or baseband signal;
a local signal generator;
a level switcher for switching an output signal level of the local signal generator; and
a controller for controlling the level switcher according to a frequency of the received signal;
wherein the local signal generator comprises a voltage-controlled oscillator and a frequency multiplier circuit for multiplying a frequency of an output signal of the voltage-controlled oscillator; and

wherein the local signal generator includes a phase-locked loop circuit for controlling an oscillation frequency of the voltage-controlled oscillator, and the controller controls the voltage-

controlled oscillator through the phase-locked loop circuit by using a control signal, and also controls the level switcher by using another control signal corresponding to the control signal.

4. (Original) A radio-frequency receiver as claimed in claim 1,
wherein the level switcher comprises a regulator and a switch for varying an output voltage of the regulator, and varies a gain of the frequency multiplier circuit by using the output voltage of the regulator.

5. (Original) A radio-frequency receiver as claimed in claim 1,
wherein the radio-frequency receiver is for receiving digital satellite broadcast.

6. (Original) A radio-frequency receiver as claimed in claim 1,
wherein the local signal generator comprises a plurality of VCOs and a VCO switcher for switching among the VCOs so that one of the VCOs is selected and connected to the frequency multiplier circuit at a time.

7. (Original) A radio-frequency receiver as claimed in claim 6,
wherein the controller controls both the level switcher and the VCO switcher according to the frequency of the received signal.

8. (Currently amended) A method of controlling a radio-frequency receiver comprising the steps of:

selecting a frequency for receiving a radio-frequency signal;
generating a local signal using a local signal generator;
providing a mixer for mixing ~~the~~ a received radio-frequency signal with the local signal to convert the radio-frequency signal into an intermediate-frequency signal or baseband signal;
and
controlling an output signal level of the local signal generator based on ~~a~~ the selected frequency ~~of the received signal~~.

9. (Previously presented) The method of claim 8 wherein said step of generating a local signal using a local signal generator comprises the steps of generating a voltage controlled oscillator signal using a voltage controlled oscillator and multiplying the voltage controlled oscillator signal by a multiplier.

10. (Previously presented) The method of claim 9 wherein said step of controlling an output signal level of the local signal generator includes the step of holding the multiplier constant.